

BEAMER 6 V2 (LCG-1212S) DMX CHART

➤ DMX Channels

4CH	5CH	6CH	7CH	9CH	12CH	VALUE	FUNCTION
-	CH1	-	CH1	CH1	CH1	0-255	Dimming all
CH1	-	CH1	CH2	CH2	CH2	0-255	Red
CH2	-	CH2	CH3	CH3	CH3	0-255	Green
CH3	-	CH3	CH4	CH4	CH4	0-255	Blue
-	CH2	CH4	CH5	CH5	CH5	0-255	Amber
CH4	CH3	CH5	CH6	CH6	CH6	0-255	White
-	CH4	CH6	CH7	CH7	CH7	0-255	UV
-	-	-	-	CH8	CH8	0-5	No strobe
						6-20	Not synchronous strobe(slow to fast)
						21-60	Synchronous strobe(slow to fast)
						61-100	Electronic Sinewave(slow to fast)
						101-140	Random Strobe(slow to fast)
						141-180	Opening pulse(slow to fast)
						181-220	Closing pulse(slow to fast)
						221-255	Electronic Squarewave(slow to fast)
-	-	-	-	-	CH9(CH 9 prior to CH11)	0-10	No effect
						11-15	CT01(call custom color setting CT01)
						16-20	CT02
						21-25	CT03
						26-30	CT04
						31-35	CT05
						36-40	CT06
						41-45	CT07
						46-50	CT08
						51-55	CT09
						56-60	CT10
						61-65	AUTO 1 (R,G,B,A,W,UV,RG,RB,GB,AW,WUV,AUV)
						66-70	AUTO 2 (R↑,R↓,G↑,G↓,B↑,B↓,A↑,A↓,W↑,W↓,UV↑,UV↓)
						71-75	AUTO 3 (R↑G↑,R↓G↓,R↑B↑,R↓B↓,B↑G↑,B↓G↓)
						76-80	AUTO 4 (R↑G↑B↑W↑,R↓G↓B↓W↓)
						81-85	AUTO 5 (Rainbow effect: B,BG↑,BG,B↓G,G,GR↑,GR,G↓R,R,RB↑,RB,R↓ B)
86-90	CHASE 1						

						91-95	CHASE 2
						96-100	CHASE 3
						101-110	Reserved
						111-200	R:111-115,G:116-120,B:121-125,A:126-130,W:131-135,UV:136-140,YELLOW:141-145,PINK:146-150,CYAN:151-155,ORANGE:156-160,VIOLET:161-165,GOLDEN:166-170,2700K:171-175,3200K:176-180,4000K:181-185,5500K:186-190,6500K:191-195,RGBW:196-200
						201-255	Reserved
-	-	-	-	-	CH10	0-255	0-255(S),(speed of AUTO, fast to slow, when AUTO1-AUTO5 effective)
						0-10	No effect
						11	Blue (Blue=full, Red+Green=0)(step)
						12-50	Red=0, Green->up,Blue =full(proportional)
						51	Light Blue (Red=0, Green=full, Blue =full)(step)
						52-90	Red=0, Green=full, Blue->down(proportional)
						91	Green (Red=0, Green=full, Blue =0)(step)
						92-130	Red->up, Green=full, Blue=0(proportional)
						131	Yellow (Red=full, Green=full, Blue=0)(step)
						132-170	Red=full, Green->down, Blue=0(proportional)
						171	Red(Red=full, Green=0, Blue=0)(step)
						172-210	Red=full, Green=0, Blue->up(proportional)
						211	Magenta (Red=full, Green=0, Blue=full)(step)
						212-250	Red -> down, Green=0, Blue=full(proportional)
						251-255	Blue (Red=0, Green=0, Blue=full)(step)
						0-10	Use the dimmer mode which menu had set up
						11-20	Linear curve and not smooth
						21-30	Square law curve and not smooth
						31-40	Inverse square law curve and not smooth
						41-50	S-curve and not smooth
						51-60	Linear curve and smooth
						61-70	Square law curve and smooth
						71-80	Inverse square law curve and smooth
						81-90	S-curve and smooth
						91-255	Use the dimmer mode which menu had set up